

## PL-SAM1LT



**Powerline TLZ (staircase time switch) actuator with 1 channel. 53x43 mm, 25 mm deep for mounting in 58 mm switch boxes. Off delay settable from 1 minute to 120 minutes. Switch-off early warning settable. 1 NO contact not potential free 10A/250V AC, incandescent lamps 2000 watts. Sensor input 230V. Standby loss only 0,5 watt. To control and switch at the same place.**

Two rotary switches are located on the front for address assignment:

**The left rotary switch defines the group address g with 16 alphabetical values from A to P.**

**The right rotary switch determines the off-delay time.**

Above it is a slide switch which acts **as a configuration switch with positions 0, 1 and 2.**

Position 0: Pushbutton at sensor input with subsequent switching.

Position 1: Same as Position 0 but with switch-off early warning.

Position 2: A change-over switch is evaluated as a pushbutton.

To the left of the rotary switches is a red LED which indicates all activities.

Next to it is a reset pushbutton and to the right of that is a service pin. For functions, please refer to the operating instructions.

The terminals located above are plug-in terminals for conductor cross-sections of 0.2 mm<sup>2</sup> to 1.5 mm<sup>2</sup>.

Typical connections on page 4-10.

**PL-SAM1LT**

Powerline TLZ actuator 1 channel with  
sensor input 230V

EAN 4010312316702

**105,40 €/pc.**