

PL-AMD10V



Powerline dimmer actuator 1-10V. 53x43 mm, 25 mm deep, for mounting in 58 mm switch boxes. To switch and/or dim via a 1-10V interface. 1 NO non-floating contact 600 VA. Standby loss only 0,5 watt. To activate and dim at different places.

Current sink of max. 30mA for active and passive electronic ballasts.

A Powerline sensor input is required for activation.

Two rotary switches are located on the front for address assignment:

The left rotary switch defines the group address g with 16 alphabetical values from A to P.

The right rotary switch defines the element address e with 16 numerical values from 0 to 15.

Above it is a slide switch which has no function here.

To the left of the rotary switches is a red LED which indicates all activities. Next to it is a reset pushbutton and to the right of that is a service pin. For functions, please refer to the operating instructions.

The terminals located above are plug-in terminals for conductor cross-sections of 0.2 mm² to 1.5 mm².

Typical connections on page 4-10.

PL-AMD10V

Powerline dimmer actuator 1-10V

EAN 4010312316726

105,40 €/pc.

Recommended retail prices excluding VAT.