


# Wireless Weather Data Transmitter Module FWS61

**Eltako**  
ELECTRONICS

## FWS61-24 V DC



### Wireless weather data transmitter module for the seven weather items sent by the multisensor MS. With internal antenna. Only 0.3 watt standby loss.

For installation. 45 mm long, 45 mm wide, 18 mm deep.

Power (24 V DC) is supplied by the switch mode power supply unit SNT61-230V/24V DC-0,25A (33 mm deep, 45 mm long, 55 mm wide). This switching power supply unit simultaneously supplies the multisensor MS including the heating of the rain sensor.

It is possible to use a deep UP box for the two devices.

This weather data transmitter module receives the seven momentary readings of the weather items: brightness (from three cardinal points), twilight, wind, rain and ambient temperature by cable J-Y (ST) Y 2x2x0,8 from the multisensor MS attached to the outside of the building. The readings are sent in the form of wireless telegrams over the Eltako wireless network with the priorities listed below. Evaluation is carried out by the Wireless Building Visualisation and Control Software GFVS, the wireless multifunction sensor relay FMSR14, the actuators FSB14 and FSB71 as well as the wireless weather data display FWA65D.

When the supply voltage is applied, a teach-in telegram is sent immediately and two status telegrams containing the momentary values are sent approx. 60 seconds later. At least every 10 minutes, but also:

**Brightness values** West, South and East each from 0 to 99 kLux if a change of minimum 10% occurs.

**Twilight values** from 0 to 999 Lux if a change of minimum 10% occurs.

**Wind speeds** from 0 to 70m/s. From 4m/s to 16m/s, the momentary values are sent immediately 3 times at intervals of 1 second. After that, further value increases are sent within 20 seconds. Dropping wind speeds are sent progressively delayed by 20 seconds.

**Rain** values at the start are sent immediately 3 times. After the rain stops, a telegram is sent within 20 seconds.

**Temperature** values from -40.0°C to +80.0°C are sent every 10 minutes together with all the other values in a status telegram.

**Monitoring multisensor function and line break.** If the weather data message from multisensor MS is not sent for 5 seconds, the FWS61 immediately sends an alarm telegram which is repeated every 30 seconds. The alarm telegram can be taught-in as a switch telegram in an actuator to initiate further action as required. In addition, the two status telegrams containing the values brightness 0 Lux, twilight 0 Lux, temperature -40°C (frost), wind 70m/s and rain are sent.

When a message is again detected from the multisensor MS, the alarm stops automatically.

## FWS61-24 V DC

Wireless weather data transmitter module

EAN 4010312301937

**65,10 €/pc.**

## Multi sensor MS



The MS multi sensor sends the current weather details, including brightness (from three points of the compass), wind, rain and frost, to the weather data transmitter module FWS61 connected in series once per second. A standard telephone wire is sufficient as connecting lead: J-Y(ST)Y 2x2x 0,8 or equivalent. 100m line length is permitted.

Solid plastic housing, LxWxH = 118x96x77mm. Degree of protection IP44.

Temperature at mounting location -30°C to +50°C.

A power supply unit FSNT61-24V/6W is required for the power supply, including heating of the rain sensor. This simultaneously supplies the wireless weather data transmitter module FWS61-24V DC.

## Multi sensor MS

EAN 4010312901731

**246,60 €/pc.**

## SNT61-230V/24V DC-0,25A



### Rated capacity 6 W. Standby loss 0.1 watt only.

Built-in device for installation. 45 mm long, 45 mm wide, 33mm deep.

Input voltage 230V (-20% up to +10%). Efficiency 82%.

Stabilised output voltage ±1%, low residual ripple.

Short-circuit proof.

Overload protection and over-temperature switch-off by means of swichting off with automatic switching-on after fault clearance (autorecovery function).

## SNT61-230V/24V DC-0,25A

EAN 4010312301326

**45,00 €/pc.**

Recommended retail prices excluding VAT.