


FPLG14

min

RS485



Wireless Powerline gateway. Bidirectional. Standby loss only 0.4 watt.

Modular device for DIN-EN 60715 TH35 rail mounting.

2 module = 36mm wide, 58mm deep.

Supply voltage 230V.

Connection to the Eltako-RS485 bus. Bus cross wiring and power supply with jumper.
This gateway translates wireless and Powerline telegrams in both directions.


Operation in conjunction with FAM14 or FTS14KS.

All Powerline telegrams from the electricity wiring system are automatically translated into RS485 bus telegrams and may also be sent as wireless telegrams by connected FTD14 devices.

Only wireless and RS485 bus telegrams taught into the FPLG14 are translated into Powerline telegrams and modulated onto the electricity wiring system. Up to 120 different addresses. Teach-in takes place by means of rotary switches on the front of the devices or using the PCT14 as described in the user's manual.

GFVS control functions for dimming, heating and shading are also possible.

Function rotary switches



Standard setting ex works.

FPLG14

Wireless Powerline gateway

EAN 4010312316771

91,60 €/pc.

Recommended retail prices excluding VAT.