


## ER61-UC



**1 CO contact potential free 10A/250V AC,  
incandescent lamp load up to 2000W. No standby loss.**

For installation. 45mm long, 45mm wide, 18mm deep.

State-of-the-art hybrid technology combines advantages of nonwearing electronic control with high capacity of special relays. Universal control voltage 8 to 230V UC. Low switching noise.

**By using a bistable relay coil power loss and heating is avoided even in the on mode.**


The relay contact can be open or closed when putting into operation. It will be synchronised at first operation.

**This relay is not suitable to feed back the switching voltage signal of a dimmer switch.  
Use only relays ESR12DDX-UC, ESR12NP-230V+UC or ESR61NP-230V+UC for this purpose.**

The electronics does not have an internal power supply and therefore no standby loss.

The microcontroller is activated when the control contact closes. This switches the bistable relay to the correct direction. The bistable relay switches back either when the control contact opens or when the control voltage falls.

### Typical connection



Technical data page 12-13.

**ER61-UC**

1 CO 16A

EAN 4010312205358

**38,60 €/pc.**

Recommended retail prices excluding VAT.