



BPD

Blisterpack dimming

Blisterpack dimming with wireless pushbutton F4T65 and universal dimmer switch FUD61NPN-230V. Smart Home sensor and Smart Home actuator.

F4T65: 4-way wireless pushbutton pure white glossy for single mounting 84x84x16mm or mounting into the E-design switching system. Generates the power for wireless telegrams itself when the button is pressed, therefore there is no connecting wire and no standby loss.

Wireless pushbuttons with one rocker can transmit two evaluable signals: press rocker up and press rocker down.

The mounting base can be screwed onto a flat surface or glued to the wall, on glass or on furniture using the enclosed adhesive foil. Use the sleeves in the 55 mm socket box for screw mounting.

FUD61NPN-230V: Universal dimmer switch, 300W power MOSFET. Automatic lamp detection. Only 0.7 watt standby loss. With adjustable minimum brightness or dimming speed. With switching operation for light alarm clocks, children's rooms and snooze function. Additionally with light scene control. Encrypted wireless, bidirectional wireless and repeater function are switchable.

For installation. 45 mm long, 45 mm wide, 33 mm deep.

Universal dimmer switch for lamps up to 300W, dependent on ventilation conditions.

Dimmable energy saving lamps ESL and dimmable 230V-LED lamps, additionally dependent on the lamps electronics.

Zero passage switching with soft ON and soft OFF to protect lamps.

Supply voltage, switching voltage and control voltage local 230V. No minimum load.

The brightness level is stored on switch-off (memory).

BPD

Blisterpack dimming

EAN 4010312314241

138,50 €/pc.